



Handleiding HIP Express randapparatuur - 5. Linksys SPA-2102

Weergaven: 655 Laatste update: 2013-08-14 10:58

2.2.2 Linksys SPA-2102



Dit is een ATA met twee analoge telefoonpoorten en een extra netwerkaansluiting. Getest met Firmware: 5.2.10

Stap 1

Configuratie:

LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Phone Adapter Configuration

Router Voice

Status Wan Setup [Admin Login](#) [basic](#) [advanced](#)

Kies rechts bovenin voor 'Admin Login'. Klik daarna op 'advanced'.

Resultaat:

Resultaat:

LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Phone Adapter Configuration

Router Voice

Status Wan Setup Lan Setup Application [User Login](#) [basic](#) [advanced](#)

Stap 2

Stel onder Router » Wan Setup een NTP-server in:

Router Voice

Status Wan Setup Lan Setup Application [User Login](#) [basic](#) [advanced](#)

Internet Connection Settings

Connection Type:

Static IP Settings

Static IP: NetMask:

Gateway:

PPPoE Settings

PPPoE Login Name: PPPoE Login Password:

PPPoE Service Name:

Optional Settings

HostName: Domain:

Primary DNS: Secondary DNS:

DNS Server Order: DNS Query Mode:

Primary NTP Server: Secondary NTP Server:

DHCP IP Revalidate Timer: Minutes

Vul dit in:

Primary NTP-server: 0.pool.ntp.org

Step 3

Zet onder Voice » Regional de 'Time Zone' goed.

Router	Voice
Miscellaneous	
Set Local Date (mm/dd):	Set Local Time (HH/mm):
Time Zone: GMT+01:00	FXS Port Impedance: 600
Daylight Saving Time Rule: start=4/1/7;end=10/-1/7;save=1	
Daylight Saving Time Enable: yes	FXS Port Input Gain: -3
FXS Port Output Gain: -3	DTMF Playback Level: -16
DTMF Playback Length: .1	Detect ABCD: yes
Playback ABCD: yes	Caller ID Method: Belcore(N.Amer,China)
Caller ID FSK Standard: bell 202	Feature Invocation Method: Default
More Echo Suppression: no	

Step 4

Vul vervolgens onder Voice » Line 1 de gegevens in voor de SIP-registratie.

Router	Voice
Proxy and Registration	
Proxy: express.hip-service.nl	
Outbound Proxy: 89.146.63.19	
Use Outbound Proxy: yes	Use OB Proxy In Dialog: yes
Register: yes	Make Call Without Reg: no
Register Expires: 3600	Ans Call Without Reg: no
Use DNS SRV: no	DNS SRV Auto Prefix: no
Proxy Fallback Intvl: 3600	Proxy Redundancy Method: Normal

Register: yes	Make Call Without Reg: no
Register Expires: 3600	Ans Call Without Reg: no
Use DNS SRV: no	DNS SRV Auto Prefix: no
Proxy Fallback Intvl: 3600	Proxy Redundancy Method: Normal
Voice Mail Server:	Mailbox Subscribe Expires: 2147483647
Subscriber Information	
Display Name: Naam Beller	User ID: U123456
Password: 123456	Use Auth ID: yes
Auth ID: UA123456	
Mini Certificate:	
SRTP Private Key:	

Vul dit in:

Proxy and Registration

Proxy: express.hip-service.nl
Outbound Proxy: 89.146.63.19
Use Outbound Proxy: yes

Subscriber Information

Display Name: zelf te bepalen
User ID: gebruikersnaam, bijvoorbeeld U123456
Password: wachtwoord
Use Auth ID: yes
Auth ID: autorisatie gebruikersnaam, bijvoorbeeld UA123456

Vervolg: [Handleiding HIP Express randapparatuur - 6. Tiptel IP 28xs](#)